You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 CS15K8SX/AWE

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY CHASSIS	
1		AA91-05845F	ASSY CHASSIS;CS15K8SX/AWE,NIGERIA,KS1A	S.N.A
..2		AA94-12483A	ASSY PCB MAIN;CS15K8SX/AWE,KS1A,NIGERIA	
...3	C801	2401-003339	C-AL;220uF,20%,400V,GP,ST,30x35,10	
...3	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
...3	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A
...3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
...3	CN701	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
⚠ ...3	CR402S	2306-000350	C-FILM,MPPF;270NF,5%,400V,TP,26X18.5X10M	
⚠ ...3	CR410S	2301-001456	C-FILM,MPE-PPF;5.1nF,5%,1.6kV,TP,29x9x16	
⚠ ...3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ ...3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
⚠ ...3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
...3	GT301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
...3	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
⚠ ...3	IC201S	AA09-00351A	IC MICOM;TDA9381/N2/3I,SPM-802MAN4,64P,3	
...3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	S.N.A
....4		1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	S.N.A
....4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
....4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	S.N.A
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	IC801S	AA96-00242A	ASSY H/S;-,-,AA62-30186B,KA5Q0765R,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	S.N.A
...3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	S.N.A
....4		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	S.N.A
...3	IC902	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
...3	JS701	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
...3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	S.N.A
⚠ ...3	LR401S	AA27-00122A	COIL LINEARITY;90UH,90UH,L81 DR10x10,7.5	
⚠ ...3	LX801S	AA29-30001D	FILTER LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ ...3	P803S	1404-001156	THERMISTOR-PTC;90HM,+30%/-20%,220VRMS,27	
⚠ ...3	PC801S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
...3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
...3	RM901	AA32-00003A	MODULE REMOCON;SBX3087-52,38KHZ,940nm,ME	
⚠ ...3	SF101S	2904-001143	FILTER-SAW AV;38.9MHz,SIP5K,ST,18dB,B/G,	
⚠ ...3	SF102S	2904-001224	FILTER-SAW AV;38.9MHz,SIP5K,ST,16.3dB,B/	
⚠ ...3	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ ...3	T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
⚠ ...3	T801S	AA26-00043A	TRANS SWITCHING;-,-,-,AC90~260V,125/12.5	
⚠ ...3	TU01S	AA40-00070A	TUNER;TEDE9-203A,PAL,181CH,38.9MHZ,75OHM	
⚠ ...3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
...3	Z	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA95-03140A	ASSY SUB PCB-LINE STEREO;20S4,C5,15A9,K8	
....4	CN702	AA39-00095A	LEAD CONNECTOR-ASSY;,3(2)P,200MM,YBNH250	
....4	CN705	3711-002708	CONNECTOR-HEADER;NOWALL,10P,1R,2.5mm,ANG	
....4	CN706	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	CN707	AA39-00276A	LEAD CONNECTOR-ASSY;,UL1185#26,UL/CSA,6P	
....4	ICS01	1204-001713	IC-SOUND PROCESSOR;MSP3465G-B8-V3,DIP,52	
....4	XS01	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
....4		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
....4		AA97-05522A	ASSY AUTO-SUB;14S4,39,KS1A ,A2,BILINGUAL	S.N.A
.....5	CS01	2201-000180	C-CERAMIC,DISC;10NF,10%,50V,Y5V,TP,7X3MM	
.....5	CS03	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
.....5	CS06	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	CS07	2201-000982	C-CERAMIC,DISC;10NF,+80-20%,50V,Y5V,TP,4	
.....5	CS09	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
.....5	CS11	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	CS12	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	CS13	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	CS14	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	CS15	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5	CS16	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	CS17	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	CS18	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	CS19	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	CS20	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	CS21	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	CS22	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	CS23	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	CS24	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	CS25	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	CS26	2201-000112	C-CERAMIC,DISC;1.5NF,10%,50V,Y5V,TP,5X3.	
.....5	CS27	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	CS28	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	CS29	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	CS30	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	CS35	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
.....5	ICS02	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
.....5	LS01	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	LS03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	LS04	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00139A	PCB-STEREO/LINE-ST/MTS-M;DREAM-1,1L,FR-1	S.N.A
.....5	RS01	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS07	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS08	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS09	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS14	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS15	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
...3		AA97-04651A	ASSY AUTO-MAIN;CS15K8SX/ANB,KS1A,MOROCCO	S.N.A
....4	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
....4	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
....4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C104	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C105	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C107	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C108	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C110	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C113	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C115	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C117	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C118	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C119	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C120	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C121	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
....4	C203	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
....4	C204	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C205	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
....4	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C209	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C211	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C213	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C214	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
....4	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4	C229	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C231	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
....4	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
....4	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
....4	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
....4	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
....4	C310	2401-000223	C-AL;0.1UF,20%,50V,LL,TP,5X11MM,5	
....4	C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
....4	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
....4	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
....4	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
....4	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,T16X5	
....4	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
....4	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
....4	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
....4	C603	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C606	2301-000314	C-FILM,PEF;8.2nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C607	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C610	2301-000314	C-FILM,PEF;8.2nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C611	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C619	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
....4	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C707	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
....4	C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
....4	C810	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
....4	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
....4	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C816	2201-000375	C-CERAMIC,DISC;0.22NF,5%,50V,RH,TP,12.5X	
....4	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C821	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
....4	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C825	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	C903	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C904	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C910	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C911	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C912	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	CN602	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	CN707A	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
⚠ 4	CR404S	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
⚠ 4	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
....4	D101	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D103	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
....4	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D805	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4	D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
....4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ401	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
....4	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
....4	DZ803	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
....4	DZ804	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
....4	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ809	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
....4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	HIC01	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
....4	IC803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	J125	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L101	2701-000326	INDUCTOR-AXIAL;0.56UH,10%,2.3X3.4MM	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L203	2701-000127	INDUCTOR-AXIAL;15uH,10%,2.5x3.4mm	
....4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
....4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
⚠ 4	L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
....4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
....4	L701	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
....4	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	S.N.A
....4	Q101	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q102	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q203	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q803	0502-000242	TR-POWER;KSA614,PNP,25W,TO-220,TP,40-24	
....4	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	Q902	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R103	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R104	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R105	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R111	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R112	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R114	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R117	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R212	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R213	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R214	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
....4	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R225	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R301	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
....4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R306	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
....4	R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
....4	R403	2003-001093	R-METAL OXIDE(S);12Kohm,5%,2W,AF,TP,3.9x	
....4	R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
....4	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
....4	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R413	2003-002130	R-METAL OXIDE(S);15ohm,5%,2W,AF,TP,3.9x1	
....4	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
....4	R421	2008-001112	R-FUSIBLE(S);2.4ohm,5%,2W,AG,TP,3.9x12mm	
....4	R423	2004-002011	R-METAL(S);110Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R501	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R505	2008-001015	R-FUSIBLE(S);1.5ohm,5%,2W,AF,TP,3.9x10mm	
....4	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R601	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R712	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R718	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
....4	R803	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
....4	R804	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
....4	R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R808	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R814	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
....4	R815	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
....4	R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R818	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R819	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
....4	R821	2001-001125	R-CARBON(S);300KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R822	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
....4	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
....4	R826	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R830	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R832	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
....4	R837	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R838	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R839	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
....4	R840	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R843	2001-000019	R-CARBON(S);100HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R924	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R931	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R932	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RW701	2011-001133	R-NETWORK;33K/24K/75x3,5%,1/8W,X,SIP6P,	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	T101	AA26-00025A	TRANS RF;7MG,-,-,-,10pF,-,58.35MHz,7.7x7	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
....4	Z201	2903-000129	FILTER-CERAMIC;BR,4.5MHz,-,-,-,TP,-	
....4	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
....4	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
...3		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	S.N.A
...3		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
..2		AA95-01724B	ASSY SUB-A/V,FRONT;20S4,21S4,15K8,-H3,KS	
...3	CN702	AA39-20461C	LEAD CONNECTOR-ASSY;,11P,300MM,YBNH250-1	
...3	CN704A	AA39-00094A	LEAD CONNECTOR-ASSY;,3(2)P,200MM,YBNH250	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	JE601	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JR01	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3		AA97-07198A	ASSY AUTO-A/V FRONT;,KS1A,PAL,AA95-01496	S.N.A
....4	CE01	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CE02	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CE04	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	CE05	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
....4	CE08	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
....4	LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
....4	LE02	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
....4	LE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	LE05	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4	PCB	AA41-00568A	PCB-FRONT AV;S4/C5,FR-1,1L,A,1.6T,245X24	S.N.A
....4	RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP2.4X6.4M	
....4	RE02	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP2.4X6.4M	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
⚠ ..2		AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A

ASSY ACCESSORY

1		AA92-05275A	ASSY ACCESSORY;CS15K8SX/AWE,NIGERIA,KS1A	S.N.A
..2		6801-001063	CARD-REGISTRATION;-,SAMSUNG,ENG+ARAB,MOJ	S.N.A
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-01795A	MANUAL USERS;,FRE.,W/P100G,ALL1,B5,KS1A,	S.N.A
..2		AA68-01602B	MANUAL USERS;,ENG,W/P100G,ALL1,B5,KS1A,3	
..2		AA59-00104M	REMOCON;,TM59,KS2A,29,L/GRAY,NON-TTX,GRA	
..2		AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-	
..2		AA26-90001C	TRANS MATCHING;-,300ohm/75ohm,PAL,40-890	

ASSY P/MATERIAL

1		AA92-03065W	ASSY P/MATERIAL;15K8	S.N.A
..2		AA69-00744B	BAG-SHEET;-,HDPE PE FOAM,T0.015,W900,H80	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

ASSY CPT

1		AA91-03995D	ASSY CPT;CS15A9SX/SMA,MALAYSIA,-100MG	S.N.A
..2	LC801S	AA27-00077A	COIL DEGAUSSING;-,-,4.3mH,20%,70T,9OHM,-	
..2		AA91-02166D	ASSY CPT;A36QDT351X(S),15,-300MG,BARE,A	S.N.A
...3		AA27-00161A	DEFLECTION YOKE;15DF,CDY-MT1501A,ST-3,A3	
...3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
...3		AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠ ...3		AA03-00188A	CRT COLOR;A36QDT351X(S),-300mG,2.5mH,22.	
..2		AA98-70014G	ASSY TBC WIRE(P);-,15inch,NTSC,1P,KS2A/C	S.N.A

ASSY COVER REAR

1		AA90-01975Y	ASSY COVER REAR;15K8,HB G4309,SCART	S.N.A
..2		AA64-01731F	CABINET BACK;15K8,HIPS,HB,G4309	
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

ASSY COVER FRONT

1		AA90-01813Y	ASSY COVER FRONT;CS15K8SX/AWE	S.N.A
..2	AV+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	S.N.A
..2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	S.N.A
..2		AA91-00619K	ASSY CABINET FRONT;,15K8 EPP,(SPK)SV012P	
...3	KC+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	WIN+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3		AA64-01371E	KNOB POWER;15K8,ABS,HB,G3676,SVM3012	
...3		AA64-01730K	CABINET-FRONT;15K8,HIPS,HB,G4309,SV012P+	
...3		AA64-70127A	BADGE-BRAND;-,AL,-,-,L=40,SAMSUNG,SILVER	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA96-10137B	ASSY SPEAKER;-,8OHM,3W,3001-001020,AA39-	S.N.A
....4		3001-001020	SPEAKER;3W,8OHM,90DB,140HZ	
....4		AA39-20505M	LEAD CONNECTOR-ASSY;,4P,350,700MM,YSH025	
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA64-01370E	KNOB CONTROL;15K8,ABS,HB,G3676,SVM3012	
...3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	S.N.A
...3		AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3		AA64-00816B	WINDOW REMOCON;-,21A8,-,PC,V0,VIOLET,-	S.N.A
...3		AA64-00818B	INDICATOR LED;21A8,ACRYL,-,CLR,-,-,-	

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-2 CS20F1X/BWT

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY COVER FRONT	
1	-	AA90-01914C	ASSY COVER FRONT;CS20F1X/BWT	
2		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
2	CB+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
2	CB+RCA	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
2	SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	
2	-	AA63-60004G	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,GRY,T3	
2	-	AA63-60004G	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,GRY,T3	
2	-	AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	
2	-	AA91-00548G	ASSY CABINET FRONT;-,501F,BK708 RUS ML(S	
3	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
3	-	AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
3	-	AA61-60003Q	SPRING ETC-CS;-,SUS304,-,-,OD8,N5,OD8,-,	
3	-	AA64-10704C	KNOB-POWER;501F,ABS,-,-,-,HB,BLK,-,-	
3	-	AA64-10759A	KNOB-CONTROL;501F,-,-,-,-,-,-,-,AA64-107	
4		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
4		AA61-01140A	CASE-PS BOX;ANTISTATIC,PS,415,305,55	
4		AA63-70002A	SHEET;-,PE FOAM,T1.0,-,-,-,50G	
4		AA64-10705A	KNOB-CONTROL;501F,ABS,-,-,-,HB,BLK,-,-	
4		AA69-10038T	PAD-PLATE;CB DW-2,YEL,615,420,-,-,-,-	
4		AA69-40003A	MASTER CARTON;-,CB DW-3,-,620,425,370,YE	
3	-	AA64-31217X	CABINET-FRONT;DP,501F,HB,AA64-01185K	
3	-	AA64-40450B	WINDOW-REMOCON;-,501F,-,PC,V0,VIOLET,-	
3	-	AA64-40451B	INDICATOR-LED;33.501F,ACRYL,-,CLR,-,-,-	
3	-	AA64-70127F	BADGE-BRAND;NEW,AL,-,-,L40,R800,SILVER,S	
3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
2		AA96-10140B	ASSY SPEAKER;-,16OHM,3W,3001-001039,AA39	
3		3001-001039	SPEAKER;3W,16OHM,90DB,180HZ	
3		AA39-20501C	LEAD CONNECTOR-ASSY;,3(2)P,700MM,67096-0	
			ASSY COVER REAR	
1	-	AA90-02077C	ASSY COVER REAR;CS20F1X/BWT	
2	-	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	
2	-	AA64-31218E	CABINET-BACK;501F,-,-,-,-,V2,-,AA64-3109	
3		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
3		AA63-70002A	SHEET;-,PE FOAM,T1.0,-,-,-,50G	
3		AA64-31094B	CABINET-BACK;501F,HIPS,-,-,-,V2,BLK,-	
3		AA69-00190B	PAD-TYPE;CB SW-2,YEL,230,90,-,-,501F,-	
3	32	AA69-01401A	PAD-PLATE;,CB SW-2,YEL,100,100	
3	99	AA69-01410A	MASTER CARTON;,CB DW-3,YEL,100,100,100	
3		AA69-10137V	PAD;PS C=0.016,-,490,450,T18,-,507	
2		AA65-30002A	CLAMPER CORE-FBT;-,NYLON-66,V0,-,BLK,-	
2	-	AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	
			ASSY CHASSIS	
1	-	AA91-01693L	ASSY CHASSIS;CS20F1X/BWT	
2	-	AA68-00364B	LABEL-SERIAL;ALL MODEL,A/P 90G,60X30	
2	-	AA94-07596F	ASSY PCB MAIN;CS20F1,KS1A	
3	-	0202-001044	SOLDER-WIRE,;S63S-W3.0,S63S,D3,63SN/37PB	
3	-	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
3	-	0204-000166	SILICON;DCI-2577,SIO2,75%,-	
3	-	0204-001095	THINNER;#4520,-,-,-	
3	-	0202-001046	SOLDER-WIRE FLUX;CF-110VH-2A,-,-,-,-	
3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
3	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
3	C801	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
3	JS701	3722-000497	JACK-PIN;4P,3.4mm,SN,BLK,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
⚠ 3	IC201S	AA09-00354A	IC MICOM;TDA9381/N2/3I,SPM-802EEN4,64P,3	
⚠ 3	T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
3	-	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
3	-	AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	
3	-	AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	
3	-	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	
3	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	
3	-	AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	
3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	
3	IC602	AA96-50311K	ASSY H/S;-,AMP,AA62-30175D,TDA8943SF	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
4		1201-001740	IC-AUDIO AMP;TDA8943,SIL,9P,850MIL,SINGL	
3	-	AA97-03401A	ASSY ROBOT-MAIN;CS20F1,KS1A	
4	IC902	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
⚠ 4	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 4	P803S	1404-001156	THERMISTOR-PTC;90HM,+30%/-20%,220VRMS,27	
⚠ 4	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 4	CR402S	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
⚠ 4	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10	
⚠ 4	SF101S	2904-001063	FILTER-SAW AV;38.9MHz,SIP5K,TP,18.5dB,B/	
⚠ 4	SW801S	3403-001107	SWITCH-PUSH;250V,5A,DPST,-,KDC-A04	
⚠ 4	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ 4	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
⚠ 4	T801S	AA26-00134A	TRANS SWITCHING;,CS21S5T,160V~260V,PM2 P	
4	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ 4	LR401S	AA27-00053A	COIL LINEARITY;-,193uH,DR10X10 C:4.35,7.	
⚠ 4	LX801S	AA29-30001B	FILTER LINE NOISE;-,-,-,-,27MH,-,-,-,ST,	
4	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
⚠ 4	TU01S	AA40-00077A	TUNER;TECC0949PL35A(S),PAL,181CH,38.9MHZ	
⚠ 4	IC801S	AA96-00242A	ASSY H/S;-,-,AA62-30186B,KA5Q0765R,-	
5		0205-000129	GREASE-SILICON;SC102,JAPAN	
5		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
5		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
5		AA62-00063A	HEAT SINK-ES;DP,-,-,-,AA62-30186B,-,-,-,	
6	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
6	-	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
6	223	AA69-01402A	PAD-PLATE;,CB DW-2,YEL,100,100	
6	-	AA69-40004F	MASTER CARTON;-,CB SW-2,-,355,265,255,YE	
4	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	
5		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
5		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
5		AA62-00074A	HEAT SINK-PS;DP,AA62-00055A,-,-,-,-,-,-,	
6	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
6	-	AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
6	-	AA69-10042F	PAD-PLATE;CB DW-2,YEL,350,260,-,-,-,-	
6	-	AA69-10116J	PAD-PLATE;CB DW-2,YEL,345,40,-,-,-,-	
6	-	AA69-40004A	MASTER CARTON;-,CB DW-3,-,355,265,175,YE	
4	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
4	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	
5		1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
5		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
5		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
4	-	AA97-04779A	ASSY AUTO-MAIN;CS20F1,KS1A	
5	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D804	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	
5	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
5	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 5	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	D807	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
5	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
5	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
5	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
5	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
5	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
5	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
5	D805	0402-001443	DIODE-RECTIFIER;EGP20K,800V,2A,DO-15,TP	
5	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
5	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
5	DZ803	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
5	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
5	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
5	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
5	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
5	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
5	DZ401	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
5	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
5	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
5	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
5	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
5	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
5	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
5	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
5	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
5	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
5	Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
5	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
5	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
5	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
5	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q703	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
5	R710	2001-000004	R-CARBON;200KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
5	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
5	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
5	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
5	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
5	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R213	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R938	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R601	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R116	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R214	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R115	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R704	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R602	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R225	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
5	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R831	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	R806	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R840	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R808	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
5	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
5	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 5	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
5	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
5	R413	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
5	R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
5	R827	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
5	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
5	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
5	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
5	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
5	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
5	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
5	R811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
5	R812	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
5	R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R306	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
5	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
5	R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
5	R302	2004-004969	R-METAL(S);1.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
5	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
5	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
5	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
5	R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
5	R814	2008-001086	R-FUSIBLE(S);3.3ohm,5%,2W,AG,TP,3.9x12mm	
5	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
5	R421	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
5	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
⚠ 5	CR409S	2201-000406	C-CERAMIC,DISC;0.27NF,10%,2KV,Y5P,TP,6.3	
5	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
5	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
5	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
5	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
5	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
⚠ 5	CR404S	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
5	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
5	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
5	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
5	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
5	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
5	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
5	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
5	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
5	C615	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nF,20%,16V,Y5R,TP	
5	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
5	C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C826	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C911	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C226	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
5	C227	2301-000014	C-FILM,PEF;6.8nF,5%,100V,TP,5.8x12.5mm,5	
5	C606	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
5	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
5	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
5	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
5	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
5	C603	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
5	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
5	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
5	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
5	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
5	C904	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
5	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
5	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
5	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
5	C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
5	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
5	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
5	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
5	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
5	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
⚠ 5	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
5	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
5	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
5	C310	2401-000223	C-AL;0.1UF,20%,50V,LL,TP,5X11MM,5	
5	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
5	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
5	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
5	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
5	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
5	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
5	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
5	C708	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
5	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C709	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
5	C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
5	C212	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
5	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
5	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
5	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
5	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
5	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
5	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
5	C110	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
5	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
5	C203	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
5	C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
5	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
5	C209	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C213	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C214	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C229	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C903	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C910	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
5	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
5	C206	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
5	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
5	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
5	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
5	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
5	C821	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
5	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
5	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
5	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
5	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
5	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
5	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
5	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
5	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
5	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
5	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
5	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
5	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
5	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
5	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
5	X901	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
5	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
5	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
5	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
5	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
5	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
5	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
5	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ 5	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
5	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
5	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
5	CN601	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
5	C107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	C507	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	C508	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	C912	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	D202	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
⚠ 5	D802	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J101	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J102	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J103	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J104	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J105	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J106	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J108	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J109	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J110	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J112	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J113	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J114	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J115	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J116	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J117	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J120	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J121	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J122	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J124	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J126	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J127	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J128	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J129	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J130	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J131	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J132	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J133	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J134	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J135	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J136	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J138	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J139	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J140	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J141	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J143	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J145	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J146	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J147	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J148	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J149	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J150	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J151	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J152	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J153	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J154	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J155	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J156	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J157	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J158	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J159	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J160	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J162	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J163	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J164	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J167	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J168	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J169	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J170	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J171	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J173	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J174	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J175	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J176	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J177	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J179	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J180	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J182	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J183	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J184	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J185	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J186	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J187	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J189	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J190	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J192	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J193	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J195	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J196	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J198	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J199	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J200	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J204	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J207	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J209	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J211	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J212	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J401	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J601	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J603	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J705	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J711	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J803	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J806	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J807	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J812	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J814	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J902	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	J913	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	JK01	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	JK02	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	JK03	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	JK04	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	L910	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
⚠ 5	NT801S	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R101	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R102	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R229	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R309	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R406	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
⚠ 5	R422S	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R507	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R508	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R509	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R703	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R705	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R805	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	R850	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
5	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
5	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
5	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
5	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
5	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
5	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
5	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
5	GT401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
5	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	
5	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	
⚠ 2	-	AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	
3		AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	

ASSY CPT

1	-	AA91-02500A	ASSY CPT;CS20F1X/BWT	
2	-	AA27-20003Y	COIL DEGAUSSING;-,20,15.2ohm,28T,L2170,E	
2	-	AA91-02167M	ASSY CPT;A48ER41X02,20,+380MG,ITC,SEB	
3		0203-001303	TAPE-ACETATE;#1554,T0.25MM,W19MM,L30M,WH	
⚠ 3		AA03-10029W	CRT COLOR;A48KRD82X(H),+380mG,2.20mH,30.	
3		AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
3		AA27-50004W	DEFLECTION YOKE;,DSE-1992LL(1HG),PCL,A48	
3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	
3		AA71-00003A	STICK FERRITE;,T0.35,W5.0,L90.0,D/K,15.0	
3		AA71-00004A	STICK FERRITE;,T0.35,W10.07,L100,D/K,25	
2	-	AA98-70014B	ASSY TBC WIRE(P);-,20,NTSC,1P,-	

ASSY LABEL

1	-	AA92-02827L	ASSY LABEL;CS20F1X/BWT
2	PK2211	AA68-00526A	LABEL-RATING;ART PAPER(90),ALL MODEL,LAM
2	-	AA68-01376C	LABEL-CRT;CIS ALL,HOLOGRAM,AUTO-VOLTAGE,

ASSY BOX

1	-	AA92-03004C	ASSY BOX;CS20F1X/BWT
2	AP2527	AA68-01290A	LABEL-BOX;ALL RUSSIA,A/P 90(G),-,-,L250,
2	-	AA69-51112T	PACKING CASE;501F,D-1 BB,-,-,-,-,-,YEL,-

ASSY P/MATERIAL

1	-	AA92-03166C	ASSY P/MATERIAL;CS20F1X/BWT
2	ACCERY	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N
2	BOX	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N
2	-	AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X
2	-	AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,
2	-	AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-
2	-	AA69-30032C	BAG-SHEET;HDPE+PE FOAM,-,W1050,H950,-,-,
2	-	AA69-20436A	CUSHION-SET;501F,PS FOAMED,C0.02,-,-,-,-

ASSY ACCESSORY

1	-	AA92-03223L	ASSY ACCESSORY;CS20F1X/BWT
2	-	4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-
2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,
2	-	AA26-90001C	TRANS MATCHING;-,300ohm/75ohm,PAL,40-890
2	-	AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-
2	-	AA59-00198D	REMOCON;,TM59,DREAM,24,L/GRAY,MONO,NONTT
2	-	AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT
2	-	AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/
2	-	AA68-01296E	MANUAL USERS;15K2/15K9,RUS,W/P100G,KS1A/
2	-	AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/
2		AA68-02638A	LABEL SERIAL;ALL (TTSEC),90G,11,32,WHITE
2	-	AA69-30002A	BAG-SHEET;LDPE,T0.05,W240,L400,-,L-TYPE,

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-3 CS21D8X/BWT

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER FRONT

1		AA90-01835V	ASSY COVER FRONT;CS21D8X/BWT	
2	SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
2	AV+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	
2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	
2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	
2	CB+JCK	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	
2		AA63-60004G	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,GRY,T3	
2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	
2		AA91-00589B	ASSY CABINET FRONT;,21D8 CIS,(SPK)SV907P	
3	-	0201-000281	ADHESIVE-RBR;D-5250,YEL,6000CPS+-500	
3	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
3	WIN+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
3	-	AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
3	POWER	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	
3		AA63-60001X	SPACER-FELT;-,FELT,-,-,-,BLK,T0.5,-,330X	
3	-	AA64-01011B	INDICATOR LED;29D8,ACRYL,-,CLR,-,-,-	
3	-	AA64-01465A	KNOB CONTROL;DP,29D8,-,-,-,-,-,-,-,AA64-	
4		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
4		AA61-01140E	CASE-PS BOX;ANTISTATIC,PS,295,295,32	
4		AA63-70002A	SHEET;-,PE FOAM,T1.0,-,-,-,50G	
4		AA64-01012B	KNOB CONTROL;29D8,ABS,-,-,-,HB,G3676,-,S	
4		AA69-10035V	PAD-PLATE;CB DW-2,YEL,580,290,-,-,-,-	
4		AA69-40007N	MASTER CARTON;-,CB DW-3,-,590,300,315,YE	
3	-	AA64-01423E	CABINET FRONT;21D8 CIS,HIPS,-,-,-,HB,G43	
3	-	AA64-01425B	KNOB POWER;21D8,ABS,-,-,-,HB,G3676,-,SV9	
3	-	AA64-01426B	WINDOW REMOCON;21D8,PC,-,-,-,VOILET,-,-	
3	-	AA64-70123B	BADGE-BRAND;-,AL,-,-,L=50,SAMSUNG,SILVER	
3	-	AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
2		AA96-10146C	ASSY SPEAKER;-,8ohm,5W,3001-000274,350/7	
3		3001-000274	SPEAKER;5W,8OHM,90DB,160HZ	
3		AA39-20505M	LEAD CONNECTOR-ASSY;,4P,350,700MM,YSH025	

ASSY COVER REAR

1		AA90-01997V	ASSY COVER REAR;CS21D8X/BWT	
2	BACK	AA60-00091A	SPACER-FELT;-,FELT,150X10,-,-,BLK,T0.35,	
2		AA64-01422J	CABINET BACK;21D8,HIPS,V2,G4309	
2		AA65-30002A	CLAMPER CORE-FBT;-,NYLON-66,V0,-,BLK,-	
2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	

ASSY CHASSIS

1		AA91-01696A	ASSY CHASSIS;CS21D8X/BWT	
2		AA68-00364B	LABEL-SERIAL;ALL MODEL,A/P 90G,60X30	
2		AA94-07596Q	ASSY PCB MAIN;CS21D8X,KS1A	
3		0202-001044	SOLDER-WIRE.;S63S-W3.0,S63S,D3,63SN/37PB	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
3		0204-000166	SILICON;DCI-2577,SIO2,75%,-	
3		0204-001095	THINNER;#4520,-,-,-	
3		0202-001046	SOLDER-WIRE FLUX;CF-110VH-2A,-,-,-,-	
3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
3	IC902	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
⚠ 3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 3	P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ 3	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 3	CR410S	2303-001015	C-FILM,PPF;5.5nF,5%,1.6kV,TP,29x9.5x17,2	
3	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
⚠ 3	CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,	
⚠ 3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
3	C801	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
⚠ 3	SF101S	2904-001063	FILTER-SAW AV;38.9MHz,SIP5K,TP,18.5dB,B/	
⚠ 3	SW801S	3403-001107	SWITCH-PUSH;250V,5A,DPST,-,KDC-A04	
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ 3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
3	JS701	3722-000497	JACK-PIN;4P,3.4mm,SN,BLK,-	
⚠ 3	IC201S	AA09-00354A	IC MICOM;TDA9381/N2/3I,SPM-802EEN4,64P,3	
⚠ 3	T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
⚠ 3	T801S	AA26-00134A	TRANS SWITCHING;,CS21S5T,160V~260V,PM2 P	
3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ 3	LR401S	AA27-00053A	COIL LINEARITY;-,193uH,DR10X10 C:4.35,7.	
⚠ 3	LX801S	AA29-30001B	FILTER LINE NOISE;-,-,-,-,27MH,-,-,-,ST,	
3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
3		AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
⚠ 3	TU01S	AA40-00077A	TUNER;TECC0949PL35A(S),PAL,181CH,38.9MHZ	
3		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	
3		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	
3		AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	
3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
3		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	
⚠ 3	IC801S	AA96-00242A	ASSY H/S;-,-,AA62-30186B,KA5Q0765R,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
4		AA62-00063A	HEAT SINK-ES;DP,-,-,-,AA62-30186B,-,-,-	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
5	223	AA69-01402A	PAD-PLATE;,CB DW-2,YEL,100,100	
5	-	AA69-40004F	MASTER CARTON;-,CB SW-2,-,355,265,255,YE	
⚠ 3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00065A	HEAT SINK-PS;DP,-,-,-,AA62-00045A,-,-,-,	
5	-	0203-000435	TAPE-OPP MASKING;OPP,T0.07,W50,L500,YEL	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	
5	-	AA69-10165J	PAD-PLATE;CB SW-2,YEL,340,250,-,-,663,-	
5	-	AA69-40004A	MASTER CARTON;-,CB DW-3,-,355,265,175,YE	
3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	
3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	
4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	
3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	
4		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00074A	HEAT SINK-PS;DP,AA62-00055A,-,-,-,-,-,-	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
5	-	AA69-10042F	PAD-PLATE;CB DW-2,YEL,350,260,-,-,-,-	
5	-	AA69-10116J	PAD-PLATE;CB DW-2,YEL,345,40,-,-,-,-	
5	-	AA69-40004A	MASTER CARTON;-,CB DW-3,-,355,265,175,YE	
3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	
4		1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
3		AA97-04767A	ASSY AUTO-MAIN;CS21D8X,KS1A	
4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
4	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
4	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
4	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
4	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
⚠ 4	D805	0402-001443	DIODE-RECTIFIER;EGP20K,800V,2A,DO-15,TP	
4	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ803	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
4	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
4	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
4	DZ401	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
4	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
4	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
4	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q703	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
4	R710	2001-000004	R-CARBON;200KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R213	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R938	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R116	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R214	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R602	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R605	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R115	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R704	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R601	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R607	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R225	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
4	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R831	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R806	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R840	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R808	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
4	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
4	R413	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
4	R827	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
4	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
4	R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
4	R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
4	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
4	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
4	R814	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
4	R815	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
4	R811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
4	R812	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
4	R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
4	R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R306	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
4	R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
4	R421	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
4	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
4	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
⚠ 4	CR404S	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
4	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
4	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
4	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
⚠ 4	CR409S	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
4	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
4	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
4	C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C826	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C911	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C226	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
4	C227	2301-000014	C-FILM,PEF;6.8nF,5%,100V,TP,5.8x12.5mm,5	
4	C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
4	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
4	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
4	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
4	C606	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C610	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C904	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
4	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
4	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
4	C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
4	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
4	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C603	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C607	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C611	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
⚠ 4	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
4	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C619	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
4	C310	2401-000223	C-AL;0.1UF,20%,50V,LL,TP,5X11MM,5	
4	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
4	C708	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
4	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C709	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
4	C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
4	C212	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
4	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
4	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
4	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
4	C110	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
4	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
4	C203	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
4	C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
4	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
4	C209	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C213	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C214	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C229	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C903	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C910	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
4	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
4	C206	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
4	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
4	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
4	C821	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	X901	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
4	L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
4	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
4	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	CN602	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
4	C107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	C507	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	C508	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	C912	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	D202	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	D802	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J101	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J102	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J103	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J104	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J105	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J106	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J108	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J109	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J110	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J112	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J113	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J114	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J115	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J116	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J117	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J120	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J121	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J122	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J123	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J124	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J126	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J127	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J128	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J129	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J130	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J131	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J132	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J133	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J134	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J135	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J136	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J138	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J139	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J140	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J141	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J143	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J145	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J146	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J147	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J148	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J149	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J150	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J151	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J152	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J153	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J154	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J155	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J156	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J157	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J158	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J159	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J160	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J163	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J167	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J168	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J169	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J170	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J171	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J173	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J174	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J175	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J176	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J177	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J179	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J180	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J181	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J182	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J183	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J184	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J185	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J186	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J187	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J189	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J190	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J192	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J193	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J195	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J196	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J198	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J199	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J200	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J204	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J207	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J209	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J211	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J212	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J401	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J601	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J603	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J705	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J711	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J803	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J807	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J812	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J814	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J902	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	J913	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	L910	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
⚠ 4	NT801S	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R101	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R102	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R107	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R229	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R309	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R406	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
⚠ 4	R422S	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R507	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R508	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R509	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R703	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R705	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R805	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	R850	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	JK01	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	JK02	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	JK03	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	JK04	3812-001010	WIRE-NO SHEATH CU;SDACW,-,ROLL,1/0.6mm,-	
4	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
4	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	GT401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	
4	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
⚠ 2		AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	
3		AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	

ASSY CPT

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-02937A	ASSY CPT;CS21D8X/BWT	
2		AA27-00143A	COIL DEGAUSSING;,35T,90HM,21INCH,220V,20	
2		AA91-02170B	ASSY CPT;A51KQJ63X(H),21,+380MG,BARE	
3	-	0203-001303	TAPE-ACETATE;#1554,T0.25MM,W19MM,L30M,WH	
⚠ 3	-	AA03-10024T	CRT COLOR;A51KQJ63X(H),+380mG,2.28mH,22.	
3	-	AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
3	-	AA27-50004K	DEFLECTION YOKE;-,DST-2192ML(H1),ST-3,A5	
3	-	AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	
3		AA71-00003A	STICK FERRITE;,T0.35,W5.0,L90.0,D/K,15.0	
3		AA71-00004A	STICK FERRITE;,T0.35,W10.07,L100,D/K,25	
2		AA98-70014C	ASSY TBC WIRE(P);-,21',NTSC,1P,TVI	

ASSY LABEL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-02830A	ASSY LABEL;CS21D8X/BWT	
2		AA68-00491C	LABEL-CRT;CIS(20INCH OVER),A/P 100(G),C/	
2	PK2447	AA68-00526A	LABEL-RATING;ART PAPER(90),ALL MODEL,LAM	
2		AA68-01376C	LABEL-CRT;CIS ALL,HOLOGRAM,AUTO-VOLTAGE,	

ASSY BOX

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-02924V	ASSY BOX;CS21D8X/BWT	
2	AP2884	AA68-01290A	LABEL-BOX;ALL RUSSIA,A/P 90(G),-,-,L250,	
2		AA69-00724D	PACKING CASE;21D8 CIS,D-2 BB,YEL,PROGUN	

ASSY P/MATERIAL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-03087V	ASSY P/MATERIAL;CS21D8X/BWT	
2		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
2	ACCERY	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	
2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	
2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	
2		AA69-00674B	CUSHION-SET;21D8,EPS,-,-,-,-,-,C=0.02,-	
2		AA69-30032D	BAG-SHEET;HDPE+PE FOAM,-,W1200,H1200,-,-	

ASSY ACCESSORY

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-03226A	ASSY ACCESSORY;CS21D8X/BWT	
2		4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-	
2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	
2		AA26-90001C	TRANS MATCHING;-,300ohm/75ohm,PAL,40-890	
2		AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-	
2		AA59-00198F	REMOCON;,TM59,DREAM,24,L/GRAY,MONO,PAL-T	
2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	
2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	
2		AA68-01296E	MANUAL USERS;15K2/15K9,RUS,W/P100G,KS1A/	
2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	
2		AA69-30002A	BAG-SHEET;LDPE,T0.05,W240,L400,-,L-TYPE,	

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-4 CS20H2X/ELE

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY COVER FRONT	
1		AA90-03188D	ASSY COVER FRONT;CS20H2X/ELE	
2	CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWR	
2	CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWR	
2	PA+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	
2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	
2	D-COIL	AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	
2		AA96-00281A	ASSY SPEAKER;-,8ohm,6W,001034,20503B,4P5	
2		AA96-00904B	ASSY COVER P-FRONT;20H2,CS20H2S/SMA,HIPS	
3	KC+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWR	
3	WIN+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWR	
3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	
3		AA64-00738J	INLAY AV;20H2,PS SHEET,-,-,T0.3,BLK,S15A	
3		AA64-01028B	CABINET FRONT;20D8,HIPS,-,-,-,HB,G4309,S	
3		AA64-01030A	KNOB POWER;20D8,ABS,-,-,-,HB,G3676,-,-	
3		AA64-01031B	WINDOW REMOCON;20D8,PC,-,-,-,V0,VIOLET,-	
3		AA64-01032B	INDICATOR LED;20D8,ACRYL,-,CLR,-,-,-	
3		AA64-01033A	KNOB CONTROL;20D8,-,-,-,-,-,-,-,MOLD	
3		AA64-70123B	BADGE-BRAND;-,AL,-,-,L=50,SAMSUNG,SILVER	
3		AA65-30105C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
			ASSY COVER REAR	
1		AA90-03196B	ASSY COVER REAR;CS20H2X/TAW	
2		AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	
2		AA64-01029E	CABINET BACK;20D8/20H4,HIPS,HB,G4309	
			ASSY CPT	
1		AA91-02510A	ASSY CPT;CS20H3X/ELE	
2		AA27-20003X	COIL DEGAUSSING;-,20,14.4ohm,48T,L2170,	
2		AA91-02167T	ASSY CPT;A48KRD82X(H),20,+380MG,BARE	
3		0203-000432	TAPE-ACETATE;#156A,T0.25MM,W19MM,L30M,WH	
⚠ 3		AA03-10029W	CRT COLOR;A48KRD82X(H),+380mG,2.20mH,30.	
3		AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
3		AA27-00086A	DEFLECTION YOKE;-,QCP-E5101,PCL,A48KRD82	
3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	
2		AA98-70014B	ASSY TBC WIRE(P);-,20,NTSC,1P,-	
			ASSY CHASSIS	
1		AA91-04360A	ASSY CHASSIS;CS20H2X/ELE,BANGLADESH,KS1A	
2		AA94-08610A	ASSY PCB MAIN;CS20H2X/ELE,KS1A,BANGLADES	
3		0202-000008	SOLDER-WIRE;S63S-W3.0,S63S,D3,63Sn/37Pb,	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
3		0204-000166	SILICON;DCI-2577,SIO2,75%,-	
3		0204-000441	FLUX;JS95TVS,FLUX,20,-	
3		0204-000442	SOLVENT;1M-1000,C3H70H,96,-	
3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
⚠ 3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
3	IC902	1103-001200	IC-EEPROM;M24C08-WBN6,1024x8Bit,DIP,8P,3	
3	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
⚠ 3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 3	P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ 3	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
3	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
⚠ 3	CR402S	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
⚠ 3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 3	CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10	
3	C801	2401-000052	C-AL;220uF,20%,400V,GP,BK,30x35,10	
⚠ 3	SF101S	2904-001143	FILTER-SAW AV;38.9MHz,SIP5K,ST,18dB,B/G,	
⚠ 3	SF102S	2904-001224	FILTER-SAW AV;38.9MHz,SIP5K,ST,16.3dB,B/	
⚠ 3	SW801S	3403-001107	SWITCH-PUSH;250V,5A,DPST,-,KDC-A04	
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ 3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
3	CN701	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
3	JS701	3722-000497	JACK-PIN;4P,3.4mm,SN,BLK,-	
⚠ 3	IC201S	AA09-00356A	IC MICOM;TDA9381/N2/3I,SPM-802EAN4,64P,3	
⚠ 3	T801S	AA26-00043A	TRANS SWITCHING;-,-,-,AC90~260V,125/12.5	
⚠ 3	T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ 3	LR401S	AA27-00053A	COIL LINEARITY;-,193uH,DR10X10 C:4.35,7.	
⚠ 3	LX801S	AA29-30001D	FILTER LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
3		AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
⚠ 3	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.9MHZ	
3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
3		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	
3	A	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	
3	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	
3		AA65-30109A	CLAMPER CORE-FBT;-,NYLON-66,V2,-,BLK,-	
3		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	
⚠ 3	IC801S	AA96-00242A	ASSY H/S;-,-,AA62-30186B,KA5Q0765R,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
⚠ 3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	
4		0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00065A	HEAT SINK-PS;DP,-,-,-,AA62-00045A,-,-,-,	
3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	
4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	
3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	
4		1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	
4		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	
3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	
4		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	
4		1201-001159	IC-VIDEO AMP;6107JF,ZSIP,9P,-,SINGLE,-,P	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
3		AA97-06873C	ASSY AUTO-MAIN;,KS1A,NIGERIA	
4	D101	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D103	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D308	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
4	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D805	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
4	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
4	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
4	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ804	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
4	DZ803	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
4	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
4	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
4	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
4	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ401	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
4	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
4	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q203	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q101	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q102	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q402	0501-002176	TR-SMALL SIGNAL;KTD863,NPN,1W,TO-92L,TP,	
4	Q703	0504-001061	TR-DIGITAL;KRC111M,NPN,400mW,10K,TO-92M,	
4	Q902	0504-001061	TR-DIGITAL;KRC111M,NPN,400mW,10K,TO-92M,	
4	IC803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
4	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R103	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R111	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R808	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R225	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R938	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R114	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R924	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R937	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R214	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R932	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R710	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R212	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R104	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R931	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R105	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R112	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R602	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R605	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R830	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R704	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R209	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R927	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R601	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R607	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R117	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R213	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
4	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R840	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R832	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R821	2001-001125	R-CARBON(S);300KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
4	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
4	R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
4	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
4	R803	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
4	R804	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
4	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
4	R413	2003-002130	R-METAL OXIDE(S);15ohm,5%,2W,AF,TP,3.9x1	
4	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
4	R814	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
4	R815	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
4	R205	2004-001234	R-METAL;75Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R306	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
4	R819	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
4	R818	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
4	R822	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
4	R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R302	2004-004969	R-METAL(S);1.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
4	R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
4	R421	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
4	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
4	C816	2201-000375	C-CERAMIC,DISC;0.22NF,5%,50V,RH,TP,12.5X	
⚠ 4	CR409S	2201-000406	C-CERAMIC,DISC;0.27NF,10%,2KV,Y5P,TP,6.3	
4	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4	C114	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
4	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
⚠ 4	CR404S	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
4	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
4	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
4	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C912	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C105	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C108	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C117	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
4	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
4	C104	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C107	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C226	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
4	C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C826	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C911	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C810	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
4	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
4	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
4	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
4	C606	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C610	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C118	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C904	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
4	C227	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
4	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
4	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
4	C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
4	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
4	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C603	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C607	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C611	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
⚠ 4	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
4	C121	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C619	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
4	C310	2401-000223	C-AL;0.1UF,20%,50V,LL,TP,5X11MM,5	
4	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
4	C708	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
4	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C709	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
4	C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
4	C212	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
4	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
4	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
4	C110	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C113	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
4	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
4	C203	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
4	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
4	C706	2401-001264	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
4	C119	2401-001271	C-AL;4.7uF,20%,50V,GP,TP,4x7mm,5mm	
4	C120	2401-001271	C-AL;4.7uF,20%,50V,GP,TP,4x7mm,5mm	
4	C209	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C213	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C214	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C229	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C903	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C910	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
4	C206	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
4	C220	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
4	C802	2401-002284	C-AL;33uF,20%,50V,GP,TP,5x11,5	
4	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
4	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
4	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
4	C821	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
4	L203	2701-000127	INDUCTOR-AXIAL;15uH,10%,2.5x3.4mm	
4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L101	2701-000326	INDUCTOR-AXIAL;0.56UH,10%,2.3X3.4MM	
4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	Z201	2903-000129	FILTER-CERAMIC;BR,4.5MHz,-,-,-,TP,-	
4	Z202	2903-000181	FILTER-CERAMIC;BR,5.5MHz,-,-,-,TP,TPS5.5	
4	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
4	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	CN602	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
4	C507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	C508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	D202	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J101	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J102	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J103	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J104	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J105	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J106	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J110	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J112	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J113	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J114	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J115	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J116	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J117	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J118	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J120	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J121	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J122	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J123	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J124	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J126	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J127	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J128	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J129	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J130	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J131	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J132	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J133	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J134	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J135	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J136	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J138	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J139	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J140	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J141	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J143	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J145	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J146	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J147	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J148	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J149	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J150	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J151	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J152	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J153	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J154	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J155	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J156	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J157	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J158	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J159	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J160	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J163	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J164	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J167	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J168	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J169	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J170	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J171	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J173	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J174	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J175	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J176	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J177	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J179	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J180	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J181	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J182	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J183	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J184	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J185	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J186	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J187	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J189	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J190	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J192	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J193	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J195	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J196	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	J198	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J199	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J200	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J204	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J207	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J209	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J211	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J212	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J213	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J214	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J401	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J601	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J603	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J705	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J711	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J803	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J807	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J812	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J814	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J902	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	L910	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	NT801S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R101	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R102	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R229	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R309	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R406	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	R422S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R509	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R703	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R705	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	HIC01	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
4	T101	AA26-00025A	TRANS RF;7MG,-,-,-,10pF,-,58.35MHz,7.7x7	
4	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
4	EY101	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY401	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY402	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY403	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY404	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY405	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY406	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY407	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY408	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY409	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY410	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY411	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY412	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY414	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY415	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY416	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY417	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY419	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY420	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY421	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY422	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY423	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY501	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY801	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY802	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY803	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY807	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY808	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY809	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY810	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY813	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY818	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY819	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY821	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY822	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY823	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY824	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY825	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY827	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY828	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY829	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY830	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY833	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY850	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY851	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY852	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY853	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY860	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EY861	AA60-40011A	K EYELET;ID2.0,OD2.8,BST	
4	EL403	AA60-40011B	K EYELET;ID2.2,OD3.2,BSP	
4	EL404	AA60-40011B	K EYELET;ID2.2,OD3.2,BSP	
4	EL801	AA60-40011B	K EYELET;ID2.2,OD3.2,BSP	
4	EL802	AA60-40011B	K EYELET;ID2.2,OD3.2,BSP	
4	EL804	AA60-40011B	K EYELET;ID2.2,OD3.2,BSP	
4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	
4	CN401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
2		AA95-01724A	ASSY SUB-A/V,FRONT;S4,KS1A,MONO,AA95-014	
3		0202-000008	SOLDER-WIRE;S63S-W3.0,S63S,D3,63Sn/37Pb,	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
3		0204-000441	FLUX;JS95TVS,FLUX,20,-	
3		0204-000442	SOLVENT;1M-1000,C3H70H,96,-	
3	JE601	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
3	JR01	3722-001282	JACK-PIN;2P(3P),3.2mm,AU,BLK,-	
3	CN702	AA39-20461C	LEAD CONNECTOR-ASSY;,11P,300MM,YBNH250-1	
3		AA97-07199A	ASSY AUTO-A/V FRONT;,KS1A,PAL,AA95-01434	
4	RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	RE02A	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	CE04	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
4	CE01	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	LE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
4	JE01	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	PCB	AA41-00568A	PCB-FRONT AV;S4/C5,FR-1,1L,A,1.6T,245X24	
2		AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	
3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	
3		AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	

ASSY ACCESSORY

1		AA92-03223Y	ASSY ACCESSORY;CS20H3X/ELE
2		4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-
2		AA26-90001C	TRANS MATCHING;-,300ohm/75ohm,PAL,40-890
2		AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-
2		AA59-00104J	REMOCON;,TM59,SIM806E,24,L/GRAY,EX,GRAY
2		AA68-01602B	MANUAL USERS;,ENG,W/P100G,ALL1,B5,KS1A,3
2		AA69-30002A	BAG-SHEET;LDPE,T0.05,W240,L400,-,L-TYPE,

ASSY BOX

1		AA92-05173E	ASSY BOX;CS20H2S/SMA
2	TSE	AA68-01204A	LABEL-PACKING;ALL MODEL,-,-,9MM,25MM,-,-
2		AA69-00507G	PACKING CASE;20H2,D-1,YEL,KS1A ASIA NO-P
2		AA02-00013A	TAPE ETC-RIBBON;-,-,-,101CM,250MT,-,-,-

ASSY P/MATERIAL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-05178A	ASSY P/MATERIAL;CS20H2X/SMA	
2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	
2		AA69-00450A	CUSHION-SET;20D8,CASTING,TOOL,-,-,-,-	
2		AA69-30031C	BAG-SHEET;HDPE+PE FOAM,-,W1050,H950,-,20	

ASSY LABEL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1	A	AA92-05213A	ASSY LABEL;CS20H2X/SMA,MALAYSIA,KS1A	
2		AA68-01768A	LABEL-CRT;21~14,21D8,21F5,S4,PET,KT-10	
2		AA68-02274A	LABEL-RATING;,2700/1RO,58*53MM	
2		AA02-00011A	TAPE ETC-RIBBON;-,-,64CM,250MT,-,-	

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-5 CS20S5ZX/AWE

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER FRONT

1		AA90-04205C	ASSY COVER FRONT;CS20S5ZX/AWE	
2	SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
2	CB+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
2	PA+CF	AA60-10002A	SCREW-TAPPING;-,ZPC(YEL),M4,L12,RH,+,-,-	
2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	
2		AA96-00757A	ASSY SPEAKER;-,8OHM,15W,001115/00320A,35	
3		3001-001115	SPEAKER;15W,8ohm,93dB,110	
3		AA39-00105D	LEAD CONNECTOR ASSY;CT21S6,UL1007#22,UL/	
3		AA91-00320A	ASSY HOLDER SPK;PIEZO ,SILVER CAP,CT-14S	
2		AA96-00955B	ASSY COVER P-FRONT;20S5 KS1A MONO,HB,G43	
3		6002-000512	SCREW-TAPPING;RH,+,2,M4,L12,ZPC(BLK),SWR	
3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
3		AA61-60003J	SPRING-CS;-,SUS304,-,-,0D6,N7,0D6,-,-,-,	
3		AA63-00461A	GRILLE-WOOFER,L;20S3,SECC T0.5,SV704G	
4		0203-000367	TAPE-CELLULOSE;#430,-,W19,L25,CLR	
4		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
4		AA63-00411B	GRILLE-WOOFER,L;20S3,SECC,T0.5,-,-,-,-,S	
4		AA63-70002A	SHEET;-,PE FOAM,T1.0,-,-,-,50G	
4	1	AA69-01400A	MASTER CARTON;,CB SW-2,YEL,100,100,100	
4	17	AA69-01401A	PAD PLATE;,CB SW-2,YEL,100,100	
4		AA69-40013C	MASTER CARTON;-,CB DW-3,-,560,370,275,YE	
3		AA63-00462A	GRILLE-WOOFER,R;20S3,SECC T0.5,SV704G	
4		0203-000367	TAPE-CELLULOSE;#430,-,W19,L25,CLR	
4		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
4		AA63-00412B	GRILLE-WOOFER,R;20S3,SECC,T0.5,-,-,-,-,S	
4		AA63-70002A	SHEET;-,PE FOAM,T1.0,-,-,-,50G	
4	1	AA69-01400A	MASTER CARTON;,CB SW-2,YEL,100,100,100	
4	17	AA69-01401A	PAD PLATE;,CB SW-2,YEL,100,100	
4		AA69-40013C	MASTER CARTON;-,CB DW-3,-,560,370,275,YE	
3		AA63-60001L	SPACER-FELT;-,FELT,-,-,-,BLK,T0.35,-,150	
3		AA64-01767B	CABINET-FRONT;HIPS HB G4309,SV704P PET-X	
3		AA64-01769B	DECORATION-COVER;20S3,ABS HB GRAY,GD906P	
3		AA64-01770A	KNOB CONTROL;20S3,ABS HB G3676	
3		AA64-01771A	KNOB POWER;20S3,ABS HB G3676	
3		AA64-01772A	WINDOW REMOCON;20S3,PC	
3		AA64-01773A	INDICATOR LED;20S3,ACRYL	
3		AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L60,SAMSUNG	
3		AA65-30105A	CLAMP-WIRE;NYLON-66,V0,NTR,(15MM)	
3		AA64-01247B	INLAY-COVER;S4,PS SHEET,T0.5,-,-,-,GD906	

ASSY COVER REAR

1		AA90-04215B	ASSY COVER REAR;20S5,HB,G4309	
2		AA63-60001L	SPACER-FELT;-,FELT,-,-,-,BLK,T0.35,-,150	
2		AA64-01768D	CABINET-back;20s5(sein),HIPS,HB,G4309	
2	A	AA65-30008A	CLAMP-CORD;-,PE,HB,BLK,-,-	

ASSY CHASSIS

1		AA91-03963F	;CS20S5ZX/AWE,NIGERIA,KS1A	
2		0203-001123	TAPE-PAPER;#53131,T0.15,W6.0,L200000,YEL	
2		AA94-11880M	ASSY PCB MAIN;CS20S5ZX/AWE,KS1A,NIGERIA	
3		0202-000008	SOLDER-WIRE;S63S-W3.0,S63S,D3,63Sn/37Pb,	
3		0202-000187	SOLDER-WIRE FLUX;,RS60S,D1.2,63SN/37PB	
3		0202-000188	SOLDER-BAR;S63S-B20,S63A,22x335,63Sn/37P	
3		0204-000442	SOLVENT;1M-1000,C3H70H,96,-	
3		0204-001024	FLUX;DF-98TVS,-,20%,-	
3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
⚠ 3	PC801S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
3	IC902	1103-001200	IC-EEPROM;M24C08-WBN6,1024x8Bit,DIP,8P,3	
3	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,PLASTIC,5V,	
⚠ 3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 3	P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ 3	CY801S	2201-000446	C-CERAMIC,DISC,3.3NF,20%,400V,Y5U,18X8	
⚠ 3	CR402S	2306-000195	CFILM,MPPF,360NF,5%,400V,26.0X11.0X1	
⚠ 3	CX801S	2306-000318	C-FILM,MPPF,220nF,20%,250V,TP,-,22.5mm	
⚠ 3	CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10	
3	C801	2401-003030	C-AL;220uF,20%,450V,GP,BK,30x35mm,1	
⚠ 3	SF101S	2904-001143	FILTER-SAW AV;38.9MHz,SIP5K,ST,18dB,B/G,	
⚠ 3	SF102S	2904-001224	FILTER-SAW AV;38.9MHz,SIP5K,ST,16.3dB,B/	
⚠ 3	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ 3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
3	CN701	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
3	CN602	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
3	JS701	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
⚠ 3	IC201S	AA09-00351A	IC MICOM;TDA9381/N2/3I,SPM-802MAN4,64P,3	
3	T101	AA26-00025A	TRANS-IF;7MG,10pF,-,58.35MHz,7.7x7.7x12.	
⚠ 3	T801S	AA26-00043B	TRANS SWITCHING;,CS21S5T,80~280V,PM2,PL3	
⚠ 3	T444S	AA26-00119A	TRANS-FLYBACK;FSV14A004F,CT15A8,3.25MH,1	
3	T401	AA26-50001B	HORIZ.DRIVE;-,7.1MH,102UH,10-20UH,YL081,	
⚠ 3	LR401S	AA27-00053A	COIL-LINEARLITY;-,193uH,DR10X10 C	
⚠ 3	LX801S	AA29-30001D	FILTER-LINER,-,6MHz,2a,-,SQ1913	
3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
3		AA39-20010D	LEAD-CONNECTOR,ASSY;-,YFH800-01,S,1P,400	
3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,YBNH250-09,S,500	
⚠ 3	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.9MHZ	
3		AA65-30009A	CLAMP-FBT;-,ABS,V0,BLK,-,-	
3	CLAMP	AA65-30014A	CLAMP-WIRE;-,NYLON-66,V0,NTR,DATL-450-1,	
3		AA65-30109A	CLAMP-FBT;NYLON-66,V2,BLK,-,-	
3		AA65-30111A	CLAMP-WIRE;NYLON,V0,WHT,1T 15MM,ALL MODE	
⚠ 3	IC801S	AA96-00242A	ASSYH/S;POWER,-, KA5Q0765R,-,	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
4		AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
⚠ 3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		0402-001374	DIODE-RECTIFIER;SDS06U20S,200V,6A,TO-220	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00065A	HEAT SINK-PS;DP,-,-,-,AA62-00045A,-,-,-,	
5		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	
5		AA69-10165J	PAD-PLATE;CB SW-2,YEL,340,250,-,-,663,-	
5		AA69-40004A	MASTER-CARTON;-,CB DW-3,-,355,265,175,YE	
3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	
3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	
4		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	
3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	
4		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
3	IC501	AA96-50311A	ASSY-H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	
4		1201-001159	IC-VIDEO AMP;6107,ZIP,9P,300MIL,SINGLE,-	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT-SINK,PS;-,SECC,T1.0,-,33X15X30 FT-2	
3		AA97-07263E	ASSY AUTO-MAIN;CS20S5ZX/AWE,KS1A,NIGERIA	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D101	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D103	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41	
4	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41	
4	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D805	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,	
⚠ 4	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
4	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
4	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ401	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ803	0403-000699	DIODE-ZENER;TZP27B,27-30.8V,1W	
4	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ804	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
4	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
4	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
4	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
4	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
4	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q203	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,80V,60V,70	
4	Q701	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q802	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q903	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q905	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q205	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q101	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q102	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q202	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q204	0501-000389	TR-SMALL SIGNALKSC815-Y,NPN V,45V,200M	
4	Q902	0504-000123	TR-DIGITAL;KSR1010,NPN,300MW,10K,TO-92,T	
4	IC803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
4	R906	2001-000005	R-CARBON;390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R905	2001-000005	R-CARBON;390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R207	2001-000005	R-CARBON;390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R218	2001-000008	.-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R111	2001-000008	.-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R103	2001-000008	.-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4x6.4MM	
4	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4x6.4MM	
4	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4x6.4M	
4	R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4x6.4M	
4	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4x6.4M	
4	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R808	2001-000109	R-CARBON(S);470ohm,5%,1/2W,AA,TP,2	
4	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R718	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R225	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R924	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R937	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R114	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R932	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R214	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R212	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R931	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R104	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R605	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R602	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R105	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R112	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R202	2001-000689	R-CARBON;390Kohm,5%,1/8W,AA,TP,1.8x3.2m	
4	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R830	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R607	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R601	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R117	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R213	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
4	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
4	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R832	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R840	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R821	2001-001125	R-CARBON(S);300Kohm,5%,1/2W,AA,TP,2.4x6.	
4	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
4	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
4	R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
4	R403	2003-000784	R-METAL OXIDE(S);7.5KOHM,5%,2W,AD,TP,4X1	
4	R804	2003-000994	R-METAL OXIDE(S);33KOHM,5%,2W,AF,TP,3.9X	
4	R803	2003-000994	R-METAL OXIDE(S);33KOHM,5%,2W,AF,TP,3.9X	
4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
4	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
4	R413	2003-002130	R-MOX;15ohm,2W,5%,AF,TP,4x12mm	
4	R801	2003-002171	R-METAL OXIDE(S)150ohm,5%,2W,AG,TP,3.9x1	
4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
4	R423	2004-001373	R-METAL(S);100KOHM,1%,1/2W,AA,TP,2.4X6.4	
4	R306	2004-001390	R-METAL(S);1KOHM,2%,1/2W,AA,TP,2.4X6.4MM	
4	R819	2004-001390	R-METAL(S);1KOHM,2%,1/2W,AA,TP,2.4X6.4MM	
4	R818	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R424	2004-001402	R-METAL(S);6.8KOHM,1%,1/2W,AA,TP,2.4X6.4	
4	R219	2004-001914	R-METAL;39KOHM,2%,1/8W,AA,TP,1.8X3.5MM	
4	R822	2004-001983	R-METAL;2.49Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R817	2004-004089	R-METAL;123Kohm,1%,1/2W,AA,TP,2.5x6.5m	
4	R302	2004-004969	R-METAL(S);1.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R600	2006-001020	R-CEMENT;3.9OHM,5%,5W,CJ,TP,10.5X14X23	
4	R305	2008-000253	R-FUSIBLE(S)0.47ohm,5%,1W,AF,TP,3.9x10mm	
4	R304	2008-000253	R-FUSIBLE(S)0.47ohm,5%,1W,AF,TP,3.9x10mm	
4	R505	2008-001011	R-FUSEBLE,0.18OHM,2W,5%,AF,TP	
4	R824	2008-001062	R-FUSIBLE;39ohm,5%,2W,AF,TP,3.9x10	
4	R825	2008-001076	R-FUSIBLE(S);1.8ohm,5%,2W,AF,TP,3.9x10mm	
4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
4	R815	2008-001113	R-FUSIBLE(S)0.22ohm,10%,2W,AG,TP,3.9x12m	
4	R814	2008-001113	R-FUSIBLE(S)0.22ohm,10%,2W,AG,TP,3.9x12m	
4	R421	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
4	RW701	2011-001133	R-NETWORK;33K/24/75/75/75ohm,5%,1/8W,X,S	
4	C302	2201-000259	C-CERAMIC,DISC;180pF,10%,500V,Y5P,TP,6x4	
4	C816	2201-000376	C-CERAMIC,DISC;0.22nF,5%,50V,SL,TP,6.3x3	
⚠ 4	CR409S	2201-000406	C-CERAMIC,DISC;0.27nF,10%,2kV,Y5P,TP,6.3	
4	C305	2201-000556	C-CERAMIC,DISC;470PF,10%,500V,Y5P,6X3.5M	
4	C303	2201-000556	C-CERAMIC,DISC;470PF,10%,500V,Y5P,6X3.5M	
4	C908	2201-000573	C-CERAMIC,DISC;0.047nF,5%,50V,NP0,TP,5x3	
4	C909	2201-000573	C-CERAMIC,DISC;0.047nF,5%,50V,NP0,TP,5x3	
4	C408	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
4	C114	2201-000611	C-CERAMIC,DISC;56PF,5%,50V,NP0,6.3X3,5,T	
4	C503	2201-000723	C-CERAMIC,DISC;4.7nF,20%,3KV,Y5U,TP,16X5	
⚠ 4	CR404S	2201-000984	C-CERAMIC,DISC;680PF,10%,2KV,Y5P,,5MM,TP	
4	C814	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,8x5,5,T	
4	C811	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,8x5,5,T	
4	C912	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C117	2202-000127	C-CERAMIC,MLC-AXIAL;10NF,+80-20%,25V,Y5V	
4	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10NF,+80-20%,25V,Y5V	
4	C108	2202-000127	C-CERAMIC,MLC-AXIAL;10NF,+80-20%,25V,Y5V	
4	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10NF,+80-20%,25V,Y5V	
4	C105	2202-000127	C-CERAMIC,MLC-AXIAL;10NF,+80-20%,25V,Y5V	
4	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
4	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
4	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C107	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C104	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C226	2202-000829	C-CERAMIC,MLC-AXIAL;.82NF,10%,50V,Y5P,TP	
4	C911	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C810	2301-000192	C-FILM,PEF;1NF,5%,50V,5.3X10MM,5MM,TP	
4	C707	2301-000204	C-FILM,PEF;2.7NF,5%,50V,7.4X3.9X13MM,5MM	
4	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
4	C804	2301-000224	C-FILM,PEF;22NF,5%,50V,7.4X3.9X13MM,5MM,	
4	C109	2301-000224	C-FILM,PEF;22NF,5%,50V,7.4X3.9X13MM,5MM,	
4	C805	2301-000235	C-FILM,PEF;3.9NF,5%,50V,6.5X3.0X5.5MM,5M	
4	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
4	C234	2301-000342	C-FILM,PEF,2.2nF,5%,50V,TP,7.4x3.9x13mm	
4	C217	2301-000342	C-FILM,PEF,2.2nF,5%,50V,TP,7.4x3.9x13mm	
4	C904	2301-000383	C-FILM,PEF;10NF,5%,50V,TP,6X7X3.2MM,5MM	
4	C610	2301-000383	C-FILM,PEF;10NF,5%,50V,TP,6X7X3.2MM,5MM	
4	C606	2301-000383	C-FILM,PEF;10NF,5%,50V,TP,6X7X3.2MM,5MM	
4	C407	2301-000383	C-FILM,PEF;10NF,5%,50V,TP,6X7X3.2MM,5MM	
4	C118	2301-000383	C-FILM,PEF;10NF,5%,50V,TP,6X7X3.2MM,5MM	
4	C248	2301-000445	C-FILM,PEF;4.7NF,5%,50V,TP,5.5X7X3MM,5MM	
4	C227	2301-000445	C-FILM,PEF;4.7NF,5%,50V,TP,5.5X7X3MM,5MM	
4	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
4	C806	2301-001435	C-FILM,PPF;1.5NF,5%,1.2KV,TP,15x8x12.5m	
4	C312	2305-000149	C-FILM;100nF,5%,100V,7.5X4.0X5.0MM,5M	
4	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,-,5MM,TP	
4	C607	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C611	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C613	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C603	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C215	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C216	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
4	C233	2305-000289	C-FILM,MPEF;220NF,5%,63V,,5MM,TP	
⚠ 4	CR405S	2305-000382	C-FILM,MPEF;4.7NF,5%,400V,-,5MM,TP	
4	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,-,5mm,TP	
4	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,-,5mm,TP	
4	C121	2305-000412	C-FILM,MPEF;470nF,5%,63V,-,5mm,TP	
4	C231	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C618	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C619	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C803	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C819	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C913	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C230	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C103	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C204	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	C205	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C218	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C210	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C208	2306-000122	C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5	
4	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,16x7mm,7.5mm,	
4	C310	2401-000223	C-AL;100NF,20%,50V,LL,5X11MM,5MM,TP	
4	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4	C915	2401-000302	C-AL;100UF,20%,25V,GP,6X11MM,5MM,TP	
4	C823	2401-000302	C-AL;100UF,20%,25V,GP,6X11MM,5MM,TP	
4	C817	2401-000302	C-AL;100UF,20%,25V,GP,6X11MM,5MM,TP	
4	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C506	2401-000430	C-AL;10UF,20%,250V,GP,10X16,5,TP	
4	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C709	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C403	2401-000560	C-AL;1uF,20%,160V,GP,6x11mm,5mm,TP	
4	C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
4	C212	2401-000647	C-AL;2.2UF,20%,50V,BP,5X11,5,TP	
4	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,5x11,5,TP	
4	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,5x11,5,TP	
4	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,5x11,5,TP	
4	C822	2401-000711	C-AL,2200uF,20%25V,GP,TP,16x25,7.5	
4	C222	2401-000758	C-AL;220NF,20%,50V,GP,5X11MM,5MM,TP	
4	C110	2401-000914	C-AL;22uF,20%,16V,GP,5x11,5,TP	
4	C113	2401-000914	C-AL;22uF,20%,16V,GP,5x11,5,TP	
4	C827	2401-000927	C-AL;22UF,20%,250V,GP,13X20MM,5MM,T	
4	C101	2401-001101	C-AL;330uF,20%,16V,GP,8x12mm,5mm,TP	
4	C203	2401-001176	C-AL,33uF,20%,25V,GP,TP,5x11,5	
4	C802	2401-001192	C-AL,33uF,50V,GP,TP,6.3x11,5	
4	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,10x12.5mm,5m	
4	C120	2401-001271	C-AL;4.7uF,20%,50V,GP,5x11mm,5mm,TP	
4	C119	2401-001271	C-AL;4.7uF,20%,50V,GP,5x11mm,5mm,TP	
4	C910	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C903	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C229	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C214	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C213	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C209	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	C706	2401-001989	C-AL,4.7uF,20%,50V,BP,TP,5x11,5	
4	C601	2401-001998	C-AL;1000UF,20%,25V,GP,TP,10X20,5MM	
4	C206	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C306	2401-002288	C-AL;470uF,20%,25V,GP,10x16mm,5mm,T	
4	C304	2401-002288	C-AL;470uF,20%,25V,GP,10x16mm,5mm,T	
4	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20mm,5m	
4	C406	2401-002619	C-AL,47uF,20%,25V,GP,TP,5x11,5	
4	C818	2401-003028	C-AL;100UF,20%,25V,GP,6.3X11,5MM,TP	
4	C821	2401-003028	C-AL;100UF,20%,25V,GP,6.3X11,5MM,TP	
4	L904	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
4	L902	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
4	L202	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
4	L103	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
4	J142	2701-000115	INDUCTOR-AXIAL;10UH,10%,2.8X7MM	
4	L203	2701-000127	INDUCTOR-AXIAL;15UH,10%,2.5X3.4MM	
4	L404	2701-000142	INDUCTOR-AXIAL;1UH,10%,2.5X3.4MM	
4	L302	2701-000142	INDUCTOR-AXIAL;1UH,10%,2.5X3.4MM	
4	L301	2701-000142	INDUCTOR-AXIAL;1UH,10%,2.5X3.4MM	
4	L903	2701-000158	INDUCTOR-AXIAL ; 22uH,10%,2.5x3.4mm	
4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L101	2701-000326	INDUCTOR-AXIAL;560nH,10%,2.3x3.4mm	
4	L807	2701-001030	INDUCTOR-AXIAL43uH,10%,5x14mm	
4	L804	2701-001030	INDUCTOR-AXIAL43uH,10%,5x14mm	
4	X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
4	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-	
4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-	
4	Z201	2903-000129	FILTER-CERAMIC;BR,4.5MHz,-,-,-,TP,-	
4	Z202	2903-000181	FILTER-CERAMIC;BR,5.5MHz,-,-,-,TP,TPS5.5	
4	Z203	2903-001040	FILTER-CERAMIC;TR,5.5/6.0/6.5MHz,-,1dB,-	
4	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	SW905	3404-000244	SWITCH-TACT;15V,20MA,90-170GF,7.5X7MM,SP	
4	SW904	3404-000244	SWITCH-TACT;15V,20MA,90-170GF,7.5X7MM,SP	
4	SW903	3404-000244	SWITCH-TACT;15V,20MA,90-170GF,7.5X7MM,SP	
4	SW902	3404-000244	SWITCH-TACT;15V,20MA,90-170GF,7.5X7MM,SP	
4	SW901	3404-000244	SWITCH-TACT;15V,20MA,90-170GF,7.5X7MM,SP	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	J189	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J190	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J192	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J187	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J186	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J185	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J184	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J204	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J200	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J199	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J198	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J196	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J195	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J193	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J175	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J174	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J173	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J171	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J170	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J169	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J168	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J183	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J182	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J181	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J180	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J179	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J177	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J176	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R102	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R101	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	NT801S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	L910	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J902	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J814	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R509	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	R422S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R406	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R309	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R229	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J401	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J214	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J213	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J212	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J211	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J209	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J207	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J812	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J807	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J803	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J711	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J705	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J603	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J601	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J167	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J122	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J121	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J120	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J118	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J117	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J116	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J115	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J130	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	J129	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J128	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J127	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J126	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J124	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J123	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J104	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J103	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J102	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J101	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	D202	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	C508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	C507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J114	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J113	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J112	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J110	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J106	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J105	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J154	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J153	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J152	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J151	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J150	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J149	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J148	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J164	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J163	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J160	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J159	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J158	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J157	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J156	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J138	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J136	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J135	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J134	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J133	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J132	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J131	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J147	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J146	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J145	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J143	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J139	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J140	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J141	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	HIC01	AA13-20004W	IC-HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
4	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
4	EY818	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY819	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY821	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY822	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY823	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY824	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY803	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY807	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY808	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY809	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY810	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY813	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY850	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY851	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY852	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY853	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY860	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY861	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY825	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY827	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY828	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY829	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY830	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY833	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY802	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY406	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY407	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY408	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY409	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY410	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY411	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY101	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY401	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY402	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY403	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY404	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY405	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY420	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY421	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY422	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY423	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY501	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY801	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY412	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY414	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY415	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY419	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY417	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EY416	AA60-40011A	EYELET;ID2.0,OD2.8,BST	
4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	
4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	
4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	
4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	
4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	
4	GT802	AA60-40012A	PIN-GT,ASSY;T1.6,1P	
4	GT803	AA60-40012A	PIN-GT,ASSY;T1.6,1P	
4	GT804	AA60-40012A	PIN-GT,ASSY;T1.6,1P	
4		AA60-40012B	PIN-GT,ASSY;T1.6,10MM,NYLON66	
4		AA60-40012C	PIN-GT,ASSY;T1.6,5-10MM,NYLON66	
4	A	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
2		AA95-01724A	ASSY SUB-A/V,FRONT;S4,KS1A,MONO,AA95-014	
3	JE601	3722-000143	JACK-PHONE;1P,3.4MM,,MBAG	
3	JR01	3722-001282	JACK-RCA;2P(3P),3.2mm,AU,BLK,-	
3	CN702	AA39-20461C	LEAD CONNECTOR-ASSY;YBNH250-11,67096-011	
3		AA97-07199A	ASSY AUTO-A/V FRONT;,KS1A,PAL,AA95-01434	
4	RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	RE02A	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	CE04	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
4	CE01	2401-001840	C-AL;100UF,20%,16V,GP,6X11MM,5MM,TP	
4	LE04	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
4	LE01	2701-000158	INDUCTOR-AXIAL ; 22uH,10%,2.5x3.4mm	
4	JE01	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	PCB	AA41-00568A	PCB-FRONT AV;S4/C5,FR-1,1L,A,1.6T,245X24	
⚠ 2		AA96-20109B	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C250,KKP	
3		AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
3		AA61-20284A	HOLDER;-,P-CORD,PP,V0,BLK,KE-002	

ASSY CPT

1		AA91-04027A	ASSY CPT;CS20H2X/SMA,MALAYSIA,0MG	
2		AA27-20003X	COIL-DEGAUSSING;-,20,14.4ohm,48T,L2170,	
2		AA91-04028A	ASSY CPT;CS20H2X/SMA,MALAYSIA,0MG	
3		0203-000432	TAPE-ACETATE;#156A,T0.25mm,W19mm,L30M,-	
⚠ 3		AA03-10029Y	CRT-COLOR -,A48KRD82X(H),-300mG,20,90de	
3		AA27-00002A	MAGNET-CONVERGENCE;-,NY-291,29.1MM	
3		AA27-00267A	DEFLECTION YOKE;-,CDY-BT2022,S/T,20,29.	
3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,BLK,V0 W12,-	
3		3309-000002	MAGNET-SHEET;5x20x80mm,UL94V-0,2	
2		AA98-70031A	ASSY-TBC,WIRE;DP,20,PAL,1P	

ASSY ACCESSORY

1		AA92-06799D	ASSY ACCESSORY;CS20S5ZX/AWE,NIGERIA,KS1A	
2		4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-	
2		AA26-90001C	TRANS-MATCHING;-,300OHM/75OHM,PAL,40-890	
2		AA42-10001M	ANT-ROD;3S,770mm,BRN,UL/CSA	

Level	Loc. No.	Code No.	Description ; Specification	Remark
2		AA59-00104J	REMOCON;-,TM59,SIM806E,25,L/GRAY,EX,GRAY	
2		AA68-01602A	MANUAL USERS;,ENG,W/P100G,ALL1,B5,KS1A,3	
2		AA68-01795A	MANUAL USERS;,FRE.,W/P100G,ALL1,B5,KS1A,	
2	A	AA69-30002A	BAG-SHEET;LDPE,T0.05,W240,L400,-,L-TYPE,	

ASSY BOX

1		AA92-06879C	ASSY BOX;CS20S5ZX/AWE	
2	SAVINA	AA68-50509A	LABEL-BOX A/P 90(G),ALL MODEL,-,WHT	
2		AA69-00988A	PACKING CASE;20S3,D-1 BB,YEL,M-ASIA	

ASSY P/MATERIAL

1		AA92-06899A	ASSY P/MATERIAL;20S5	
2		0203-001160	TAPE-FILAMENT;SCOTCH#8915,T0.16,W48,L55M	
2		0203-001096	TAPE-CELLULOSE;#301,T0.06,W75,L400,WHT	
2		AA60-40006A	PIN-STAPLE;-,-,H18,33X17.8X2.4,-,AUTO	
2		AA69-00989A	CUSHION SET;TOOL,20S3(SAVINA),CASTING	
2	A	AA69-01428A	BAG-SHEET ;HDPE-FORM,T0.02,W1200,L11,PRI	

ASSY LABEL

1	A	AA92-07324A	ASSY LABEL;,.	
2		AA68-01660A	LABEL-CRT;21~14,21D8,21F5,A/P 100(G),6	
2		AA68-01881A	LABEL-QMS,135*100mm,1140/1ROL	
2	SAVINA	AA68-02274A	LABEL-RATING;,2700/1RO,58*53MM	
2		AA83-00007A	PREMIUM RIBBON,FOR ART PARPER	
2	A	AA83-00008A	PREMIUM RIBBON, FOR PE	

MEMO